

Hitachi Storage Plug-in for Containers v3.17.0 Release Notes

About this document

This document (RN-92ADPTR141-26, October 2025) provides late-breaking information about Hitachi Storage Plug-in for Containers v3.17.0 release. It includes information that was not available at the time the technical documentation for this product was published, as well as a list of known problems and solutions.

Intended audience

This document is intended for customers and Hitachi Vantara partners who license and use Hitachi Storage Plug-in for Containers.

Getting help

[Hitachi Vantara Support Connect](#) is the destination for technical support of products and solutions sold by Hitachi Vantara. To contact technical support, log on to Hitachi Vantara Support Connect for contact information: https://support.hitachivantara.com/en_us/contact-us.html.

[Hitachi Vantara Community](#) is a global online community for customers, partners, independent software vendors, employees, and prospects. It is the destination to get answers, discover insights, and make connections. **Join the conversation today!** Go to community.hitachivantara.com, register, and complete your profile.

Comments

Please send comments to doc.feedback@hitachivantara.com. Include the document title and number, including the revision level (for example, -07), and refer to specific sections and paragraphs whenever possible. All comments become the property of Hitachi Vantara LLC.

Thank you!

Accessing product documentation

Product user documentation is available on the Hitachi Vantara documentation website: <https://docs.hitachivantara.com>. Check this site for the most current documentation, including important updates that may have been made after the release of the product.

Accessing product downloads

Product software, drivers, and firmware downloads are available on the Hitachi Vantara Support Website: <https://support.hitachivantara.com>.

Log in and select Download Products and Updates to access the most current downloads, including important updates that may have been made after the release of the product.

About this release

This is a major release that adds new features.

Software and hardware support

This release supports only the hardware and software explicitly listed below.

Refer to the Product Compatibility Guide for the latest information: <https://compatibility.hitachivantara.com/products/hspc/>.

Operating Systems

Hitachi Storage Plug-in for Containers supports the following operating systems.

- Red Hat Enterprise Linux 8.2 - 8.4, 8.6 - 8.8, 8.10, 9.0, 9.2 - 9.4, 9.6
- Red Hat Enterprise Linux Core OS 4.18 - 4.20
- Ubuntu 20.04, 22.04, 24.04
- Amazon Linux 2

Note: NVMe over Fibre Channel and NVMe over TCP are supported only on Red Hat Enterprise Linux 9.x, Red Hat Enterprise Linux CoreOS, and Ubuntu.

Software

Hitachi Storage Plug-in for Containers supports the following software.

Software	Version
Kubernetes	1.30 - 1.33
Red Hat OpenShift Container Platform	4.18 - 4.20
Rancher Kubernetes Engine 2	1.30 - 1.33
Amazon Elastic Kubernetes Service	1.30 - 1.33

Storage Systems

Hitachi Storage Plug-in for Containers supports Hitachi Virtual Storage Platform family (VSP family) and Hitachi Virtual Storage Platform One Block 24, 26, 28 (VSP One B24, B26, B28) and Hitachi Virtual Storage Platform One SDS Block (VSP One SDS Block).

Item	Description	Firmware Version	Protocol
Supported systems	VSP G200, G400, G600, G800, F400, F600, F800	83-05-37 or later	Fibre Channel, iSCSI
	VSP G350, G370, G700, G900, F350, F370, F700, F900,	88-06-02 or later	Fibre Channel, iSCSI
	VSP N400, N600, N800	83-06-09 or later	Fibre Channel, iSCSI
	VSP 5100, 5500, 5100H, 5500H	90-04-04 or later	Fibre Channel, iSCSI
	VSP E590, E790, E990, E590H, E790H	93-02-04 or later	Fibre Channel, iSCSI

Item	Description	Firmware Version	Protocol
	VSP 5200, 5600,5200H, 5600H	90-08-01 or later Note: NVMe over Fibre Channel requires 90-09-21 or later.	Fibre Channel, iSCSI, and NVMe over Fibre Channel
	VSP E1090, E1090H	93-06-01 or later Note: NVMe over Fibre Channel requires 93-07-21 or later.	Fibre Channel, iSCSI, and NVMe over Fibre Channel
	VSP One B24, B26, B28	A3-04-02 or later	Fibre Channel, iSCSI, and NVMe over Fibre Channel
	VSP One SDS Block	01.08.00.0x or later	Fibre Channel, iSCSI, and NVMe/TCP

New features and important enhancements

- Support for Red Hat OpenShift Container Platform 4.20
- Support for clone operations on VSP One B20 series storage systems
- Support for `copyGroupName`, `copyPairName`, and `consistencyGroupId` optional parameters when creating a storage class for a stretched PVC
- Support for configuring multipath settings on Kubernetes nodes through a DaemonSet.

Limitations and Important Notes

- Controller model upgrade operations are not supported while the plug-in is running. To perform a controller model upgrade, you must stop the plug-in before upgrading.
- When adding or removing a storage node in Hitachi Virtual Storage Platform One SDS Block, Pods created before the change may not function correctly. To resolve this, restart HSPC, and then restart the affected Pods that were created before adding or removing the storage node.
- When removing a storage node from Hitachi Virtual Storage Platform One SDS Block, NVMe/TCP connections to the removed node may persist. To clear these connections, restart the node hosting the Pod that maintains the NVMe/TCP connection.
- When you create a secret file specifying the primary and secondary storage systems and use it to provision a Stretched PVC, you cannot later interchange the primary and secondary values.
- When using the ReadOnlyMany feature, attaching a ReadOnlyMany PVC to a Pod may result in a "read-only file system" error. You can identify this error using the command: `kubectl describe pod <pod_name>`.
Workaround: Recreate the Pod with `spec.volumes.persistentVolumeClaim.readOnly` parameter set to true in the Pod specification.
- The ReadOnlyMany access mode is not supported for NVMe over Fibre Channel.
- When using NVMe over Fibre Channel, each NVM subsystem must be dedicated to a single Kubernetes cluster. Do not share an NVM subsystem across multiple Kubernetes clusters.
- Multi-AZ configuration is not supported by the cloud model of Hitachi Virtual Storage Platform One SDS Block.
- In OpenShift virtualization, if you expand a volume that is attached as a VM disk, but the VM does not show the increased disk size, you must restart the VM for the new capacity to take effect.
- If a PVC deletion fails, you must manually delete the corresponding PV. However, if the PV contains a finalizer, its deletion will also fail. To resolve this, remove the finalizer from the PV—this will allow the deletion to succeed during a retry attempt.
- The ReadOnlyMany access mode is not supported with OpenShift virtualization.

- When using HTTPS for a storage connection with certificate verification enabled, the certificate must be installed within the container image of the Storage Plug-in for Containers.
- When using NVMe over Fibre Channel (NVMe/FC) or NVMe over TCP (NVMe/TCP), volume mounting will fail with an unmarshal JSON error if a Kubernetes or OpenShift Container Platform (OCP) node has NVMe drives directly connected through the PCIe bus. This issue occurs because the transport type pcie is not supported.
- Stretched PVC pools can be created only within a virtual storage machine.
- Mounting a PVC that is created from a stretched PVC is not supported.

Technology Preview

Technology Preview features provide early access to upcoming Hitachi Vantara adapter product innovations, so your site can test the functionality and provide feedback.

However, these features are not covered under any Hitachi Vantara support plans, may not be functionally complete, and are not intended for production use: Although technology preview updates are included with the software code, we recommend only using those features within a separate test environment. As such, technology preview information is noted in the provided user documentation so your site can determine whether to apply it to a test environment.

Because Technology Preview features are still under development, Hitachi Vantara cannot guarantee the stability or reliability of such features. While Hitachi Vantara intends to fully support Technology Preview features in future releases, we may discover that a feature does not meet the standards for enterprise viability. If this happens, we cannot guarantee that Technology Preview features will be released in a supported manner. Some Technology Preview features may only be available for specific plug-in configurations.

Hitachi Vantara may create bug reports on behalf of support cases filed by subscribed customers. These bug reports will then be forwarded to Hitachi Vantara Engineering as proposed for inclusion in a future release.

Copyrights and licenses

© 2024, 2025 Hitachi Vantara LLC. All rights reserved.

No part of this publication may be reproduced or transmitted in any form or by any means, electronic or mechanical, including copying and recording, or stored in a database or retrieval system for commercial purposes without the express written permission of Hitachi, Ltd., Hitachi Vantara, Ltd., or Hitachi Vantara LLC (collectively “Hitachi”). Licensee may make copies of the Materials provided that any such copy is: (i) created as an essential step in utilization of the Software as licensed and is used in no other manner; or (ii) used for archival purposes. Licensee may not make any other copies of the Materials.

“Materials” mean text, data, photographs, graphics, audio, video and documents.

Hitachi reserves the right to make changes to this Material at any time without notice and assumes no responsibility for its use. The Materials contain the most current information available at the time of publication.

Some of the features described in the Materials might not be currently available. Refer to the most recent product announcement for information about feature and product availability, or contact Hitachi Vantara LLC at https://support.hitachivantara.com/en_us/contact-us.html.

Notice: Hitachi products and services can be ordered only under the terms and conditions of the applicable Hitachi agreements. The use of Hitachi products is governed by the terms of your agreements with Hitachi Vantara LLC.

By using this software, you agree that you are responsible for:

1. Acquiring the relevant consents as may be required under local privacy laws or otherwise from authorized employees and other individuals; and
2. Verifying that your data continues to be held, retrieved, deleted, or otherwise processed in accordance with relevant laws.

Notice on Export Controls. The technical data and technology inherent in this Document may be subject to U.S. export control laws, including the U.S. Export Administration Act and its associated regulations, and may be subject to export or import regulations in other countries. Reader agrees to comply strictly with all such regulations and acknowledges that Reader has the responsibility to obtain licenses to export, re-export, or import the Document and any Compliant Products.

Hitachi and Lumada are trademarks or registered trademarks of Hitachi, Ltd., in the United States and other countries.

AIX, DB2, DS6000, DS8000, Enterprise Storage Server, eServer, FICON, FlashCopy, GDPS, HyperSwap, IBM, OS/390, PowerHA, PowerPC, S/390, System z9, System z10, Tivoli, z/OS, z9, z10, z13, z14, z15, z16, z/VM, and z/VSE are registered trademarks or trademarks of International Business Machines Corporation.

Active Directory, ActiveX, Bing, Excel, Hyper-V, Internet Explorer, the Internet Explorer logo, Microsoft, Microsoft Edge, the Microsoft corporate logo, the Microsoft Edge logo, MS-DOS, Outlook, PowerPoint, SharePoint, Silverlight, SmartScreen, SQL Server, Visual Basic, Visual C++, Visual Studio, Windows, the Windows logo, Windows Azure, Windows PowerShell, Windows Server, the Windows start button, and Windows Vista are registered trademarks or trademarks of Microsoft Corporation. Microsoft product screen shots are reprinted with permission from Microsoft Corporation.

All other trademarks, service marks, and company names in this document or website are properties of their respective owners.

The open source content used in Hitachi Vantara products may be found within the Product documentation or you may request a copy of such information (including source code and/or modifications to the extent the license for any open source requires Hitachi make it available) by sending an email to OSS_licensing@hitachivantara.com.